

DWDM Spacing Code Chart

100 GHz

	Frequency	λ		Frequency	λ		Frequency	λ		Frequency	λ
Code	(GHz)	(nm)	Code	(GHz)	(nm)	Code	(GHz)	(nm)	Code	(GHz)	(nm)
L66	186600	1606.60	L90	189000	1586.20	C14	191400	1566.31	C38	193800	1546.92
L67	186700	1605.74	L91	189100	1585.36	C15	191500	1565.5	C39	193900	1546.12
L68	186800	1604.88	L92	189200	1584.53	C16	191600	1564.68	C40	194000	1545.32
L69	186900	1604.03	L93	189300	1583.69	C17	191700	1563.86	C41	194100	1544.53
L70	187000	1603.17	L94	189400	1582.85	C18	191800	1563.05	C42	194200	1543.73
L71	187100	1602.31	L95	189500	1582.02	C19	191900	1562.23	C43	194300	1542.94
L72	187200	1601.46	L96	189600	1581.18	C20	192000	1561.42	C44	194400	1542.14
L73	187300	1600.60	L97	189700	1580.35	C21	192100	1560.61	C45	194500	1541.35
L74	187400	1599.75	L98	189800	1579.52	C22	192200	1559.79	C46	194600	1540.56
L75	187500	1598.89	L99	189900	1578.69	C23	192300	1558.98	C47	194700	1539.77
L76	187600	1598.04	L00	190000	1577.86	C24	192400	1558.17	C48	194800	1538.98
L77	187700	1597.19	C01	190100	1577.03	C25	192500	1557.36	C49	194900	1538.19
L78	187800	1596.34	C02	190200	1576.20	C26	192600	1556.55	C50	195000	1537.40
L79	187900	1595.49	C03	190300	1575.37	C27	192700	1555.75	C51	195100	1536.61
L80	188000	1594.64	C04	190400	1574.54	C28	192800	1554.94	C52	195200	1535.82
L81	188100	1593.79	C05	190500	1573.71	C29	192900	1554.13	C53	195300	1535.04
L82	188200	1592.95	C06	190600	1572.89	C30	193000	1553.33	C54	195400	1534.25
L83	188300	1592.10	C07	190700	1572.06	C31	193100	1552.52	C55	195500	1533.47
L84	188400	1591.26	C08	190800	1571.24	C32	193200	1551.72	C56	195600	1532.68
L85	188500	1590.41	C09	190900	1570.42	C33	193300	1550.92	C57	195700	1531.90
L86	188600	1589.57	C10	191000	1569.59	C34	193400	1550.12	C58	195800	1531.12
L87	188700	1588.73	C11	191100	1568.77	C35	193500	1549.32	C59	195900	1530.33
L88	188800	1587.88	C12	191200	1567.95	C36	193600	1548.51	C60	196000	1529.55
L89	188900	1587.04	C13	191300	1567.13	C37	193700	1547.72	C61	196100	1528.77

200 GHz

	Frequency	λ		Frequency	λ		Frequency	λ		Frequency	λ
Code	(GHz)	(nm)	Code	(GHz)	(nm)	Code	(GHz)	(nm)	Code	(GHz)	(nm)
C01	190100	1577.03	C17	191700	1563.86	C33	193300	1550.92	C49	194900	1538.19
C03	190300	1575.37	C19	191900	1562.23	C35	193500	1549.32	C51	195100	1536.61
C05	190500	1573.71	C21	192100	1560.61	C37	193700	1547.72	C53	195300	1535.04
C07	190700	1572.06	C23	192300	1558.98	C39	193900	1546.12	C55	195500	1533.47
C09	190900	1570.42	C25	192500	1557.36	C41	194100	1544.53	C57	195700	1531.90
C11	191100	1568.77	C27	192700	1555.75	C43	194300	1542.94	C59	195900	1530.33
C13	191300	1567.13	C29	192900	1554.13	C45	194500	1541.35	C61	196100	1528.77
C15	191500	1565.50	C31	193100	1552.52	C47	194700	1539.77			



GoFoton Corporation Somerset, NJ USA
 Tel. +1-732-469-9650 Fax +1-732-469-9654
West Coast Sales San Jose, CA USA
 Tel. +1-408-441-0501 Fax +1-732-469-9654

GoFoton, Inc. Tsukuba-City, Ibaraki, JAPAN
 TEL: +81-29-847-8686 FAX +81-29-847-8693
Europe Office Hoogerheide, The Netherlands
 TEL: +31 (0)164 62 04 22 FAX +31 (0)164 62 04 17